

Appl. No. 09/934,870  
Amdt. Dated June 19, 2006  
Response to Examiner Interview on June 8, 2006

Attorney Docket No. 83357.0001  
Customer No.: 26021

Amendments to the Claims:

This listing of claims will replace all prior versions, and listings, of claims in the application:

Listing of Claims:

1. (Currently Amended): An SSB radio communication system comprising:  
amplitude modulating a carrier wave in a transmitting side by using modulation inputs, wherein the modulation inputs comprise a constant amplitude, sine wave shaped reference pulse signal having a predetermined width and period, and sine wave shaped modulation pulse signals having the same width as the reference pulse signal and amplitudes representing two- or multi-value digital values based on the amplitude of the reference pulse signal,  
transmitting the amplitude modulated signals on a single side band, and  
automatically adjusting gains of received signals in a receiving side which are values of peaks of the received signals based on the reference pulse signal, wherein  
forming the period or frequency of said reference pulse signal in the transmitting side in synchronism with the carrier wave frequency, and  
determining a local carrier frequency in the receiving side, based on the period or frequency of said reference pulse signal, wherein  
said reference pulse signal is formed such that the reference pulse signal is provided with a predetermined width and a predetermined period based on said carrier wave frequency of the transmitting circuit.
2. (Cancelled).

Appl. No. 09/934,870  
Amdt. Dated June 19, 2006  
Response to Examiner Interview on June 8, 2006

Attorney Docket No. 83357.0001  
Customer No.: 26021

3. (Previously Presented): A radio apparatus comprising:  
a transmitting circuit for single side band communications, and  
means for generating modulation inputs, wherein said modulation inputs comprise a constant amplitude, sine wave shaped reference pulse signal having a predetermined width and period, and sine wave shaped modulation pulse signals having the same width as the reference pulse signal and amplitudes representing two- or multi-value digital values based on the amplitude of the reference pulse signal, wherein

said modulation inputs generated by the generating means are supplied to the transmitting circuit so as to amplitude modulate a carrier wave to transmit the amplitude modulated signals through a single side band, wherein

said reference pulse signal is formed such that the reference pulse signal is provided with a predetermined width and a predetermined period based on said carrier wave frequency of the transmitting circuit.

4. (Cancelled).

5. (Currently Amended): A radio apparatus comprising:  
an intermediate frequency amplifier for receiving communication signals carried on a single side band, and for automatically controlling the gain of the received signals,  
a demodulator for demodulating the received signals based on a local carrier wave frequency, and  
gain control means for automatically control the gain of said intermediate frequency amplifier such that a sine wave shaped reference pulse signal, which is contained in the output signals of said intermediate frequency amplifier, and which has a predetermined width and a predetermined period,

Appl. No. 09/934,870  
Amdt. Dated June 19, 2006  
Response to Examiner Interview on June 8, 2006

Attorney Docket No. 83357.0001  
Customer No.: 26021

is peak detected so that its peak value becomes a predetermined value,  
wherein

said reference pulse signal which is contained in the output  
signals of said intermediate frequency amplifier is peak detected to extract a  
row of constant period pulse signals, and wherein said local carrier wave  
frequency is adjusted based on said row of constant period pulse signals,  
wherein

said reference pulse signal is formed such that the reference pulse  
signal is provided with a predetermined width and a predetermined period  
based on said carrier wave frequency of the transmitting circuit.

6. (Cancelled).

7. (Previously Presented): A radio apparatus of claim 5, further  
comprising a low frequency amplifier disposed in the latter stage of said  
demodulator, wherein the gain of said low frequency amplifier is controlled by  
the automatic gain control means based on said reference pulse signal  
contained in the output signals of said low frequency amplifier.

8. (Original): A radio apparatus for receiving single side band  
communication signals modulated by modulation inputs, wherein said  
modulation inputs comprise a constant amplitude, sine wave shaped reference  
pulse signal, formed based on a carrier frequency, having a predetermined  
width and a predetermined period, and sine wave shaped modulation pulse  
signals having the same width as the reference pulse signal and amplitudes  
representing two- or multi-value digital values based on the amplitude of the  
reference pulse signal, the apparatus comprising,

an intermediate frequency amplifier for automatically control the  
gain of the modulated signals,

Appl. No. 09/934,870  
Amdt. Dated June 19, 2006  
Response to Examiner Interview on June 8, 2006

Attorney Docket No. 83357.0001  
Customer No.: 26021

a demodulator for demodulating the received signals,  
automatic gain control means for peak detecting said reference pulse signal contained in the output signals of said intermediate frequency amplifier, and for controlling the gain of said intermediate frequency amplifier so that its peak value becomes a predetermined value, wherein

the output of said intermediate frequency amplifier is amplitude detected by a amplitude detector means to extract a frequency component of the predetermined period of said reference pulse signal, the frequency obtained based on the frequency obtained by said amplitude detector means is mixed with the frequency of the output signal of said intermediate frequency amplifier, and the frequency representing the sum or difference therebetween is fed to said demodulator as a local carrier frequency wave.

9. (Original): A radio apparatus of claim 8, further comprising a condenser having a charging/discharging circuit to control the gain of said intermediate frequency amplifier according to a charging voltage, wherein said discharging circuit of the condenser is switched on during a period when the amplitude of said reference pulse signal increases, and switched off during at least a period of the modulation pulse signal.